

## <u>ATTENTION</u>

- DO NOT EXCEED MAXIMUM ELECTRICAL RATING LISTED ON PRODUCT NAMEPLATE.
- WIRE ACCORDING TO NATIONAL AND LOCAL ELECTRICAL CODES.
- TERMINAL BLOCK ACCEPTS 10-26 AWG (0,41-5,26mm<sup>2</sup>) WIRE.
- TO ORDER THIS JUNCTION BOX PRE-INSTALLED ON UE PRODUCTS, USE THE M433 OPTION CODE.
- TO ORDER THIS JUNCTION BOX AS A SEPERATE KIT USE ACCESSORY PART NUMBER 62169-49.

## **JUNCTION BOX ASSEMBLED KIT INCLUDES:**

- (1) JUNCTION BOX WITH GROUND SCREWS AND COVER
- (1) MOUNTED TERMINAL BLOCK
- (1) M20X1.5 STOPPING PLUG
- (1) GROUNDING TERMINAL
- M20 NYLON SEALING WASHER


## **INSTALLATION INSTRUCTIONS:**

- INSTALL SEALING WASHER (TAPERED SIDE DOWN) ONTO THE THREADS OF THE PRODUCT THE JUNCTION BOX WILL MOUNT TO.
- ROUTE WIRES INTO THE JUNCTION BOX AND TIGHTEN CONDUITS INTO POSITION.
- CUT WIRES TO DESIRED LENGTHS AND STRIP WIRES 1/4" (6mm).
- ATTACH SUPPLIED GROUND TERMINAL TO THE GROUND WIRE USING A SUITABLE CRIMPING TOOL AND SECURE IT TO THE INTERNAL GROUND SCREW.
- WIRES MAY BE ROUTED UNDER OR TO THE RIGHT OF THE TERMINAL BLOCK.
- SEE PRODUCT NAMEPLATE, BULLETIN OR INSTALLATION & MAINTENANCE MANUAL FOR WIRING UE CONTROLS. INFO. ALSO AVAILABLE AT <u>WWW.UEONLINE.COM</u>.

## FRONT VIEW WITHOUT COVER



GROUNDING TERMINAL INCLUDED SCALE 1:1



M20 SEALING WASHER INCLUDED SCALE 1:1

	В	E5852	ADDED MOUNTING HOLE DIMS. ADDED "UNDER OR" TO WIRE ROUTING INSTALLATION INSTRUCTION.	6-21-16	SR	RCI
THIS DOCUMENT IS PROPRIETARY PROPERTY OF UNITED ELECTRIC CONTROLS. UNAUTHORIZED USE IS STRICTLY PROHIBITED.	Α	E5809	FIRST ISSUE	5/11/16	RCI	RCI
	REV.	ECN#	DESCRIPTION	DATE	DRWN	APPD

ORIGINAL DATE 5-11-16

DRWN RCI

CHKD SR

APPD R. IACABONE

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES

TOLERANCES ON FRACTIONS ±1/64

2 PLACE DEC 3 PLACE DEC ANGLES ±0.010 ±0.005 ±1/2°

DO NOT SCALE THIS DRAWING

SIDE VIEW WITH COVER

M20 SS
JUNCTION BOX
KIT
INSTALLATION
INSTRUCTIONS

CONTROLS COMPANY
WATERTOWN \* MASSACHUSETTS

DWG NO Page 1 of 1

UNITED ELECTRIC

A-6271-353

ŪΕ

SCALE 1:2